

Getting Started

Terminal Camera is a comprehensive and practical software utility that provides you with a simple means of monitoring computer usage and user activity. With the help of Terminal Camera you have the possibility to track each opened application, playback all user activity within each section. It also provides you with an embedded video player so you can preview the selected action.

Contents

- [Install](#)
 - [Login](#)
 - [Buy And Register](#)
- [Management](#)
 - [Local Computer](#)
 - [LAN](#)
 - [Internet](#)
- [Search](#)
 - [Sessions List](#)
 - [Search By Program or Window Title](#)
 - [Search By Website or Url](#)
 - [Search By Disk Drive or File Path](#)
- [Statistic](#)
 - [Computer Usage](#)
 - [Program Usage](#)
 - [Website Visit](#)
- [Configuration](#)
 - [System Parameters](#)
 - [Filter Policy](#)
 - [License Info](#)
 - [Admin Password](#)
- [Advanced Features](#)
 - [JSON API](#)
 - [Enterprise Version](#)

Install


Installation of this product requires system administrator privileges.

1. Unzip compressed files you have downloaded.
2. Run **TerminalCamera.exe** to install.
3. If .NET 2.0 Framework not installed, it will be download and install automatically.

Login

Visit <http://localhost:1088> or <http://127.0.0.1:1088> by web browser.

Default account/password is **admin / admin**.



The image shows the 'Terminal Camera' login window. It has a title bar with a lock icon and the text 'Terminal Camera'. Inside, there's a large padlock icon on the left. To its right, there are two input fields: 'Account:' and 'Password:'. Above the 'Account:' field is a red text label 'Getting help online' with an arrow pointing to a help icon in the top right corner. Below the input fields are three buttons: 'Contract' (with a checkmark icon), 'Submit' (with a green checkmark icon), and 'Reset' (with a blue circular arrow icon). A red text label 'Contract us' with an arrow points to the 'Contract' button. At the bottom, there's a text box containing the email address 'support@ultragis.com'.

Buy And Register

1. **Login** to management interface by web browser.
2. Click **Buy Now** button to buy this software and MachineId will be send automatically.
3. We will send license key to you by E-Mail as soon as possible.
4. Copy and paste license key in register box and click **Register** button to register.
5. After the registration done, right panel of **Buy Now** button and adware image will be invisibly.

License Info	
Version	2.0.0
LicenseType	Trial
MachineId	97689C13F7DB0B56FF30D90770DC7324
CreateTime	2013年11月7日
ExpireTime	2013年11月22日
IsValid	true
Support	support@ultragis.com



After registration, this will be hidden.

Management

User can administrate Terminal Camera by web browser from localhost, LAN or Internet.

Local Computer

Visit <http://localhost:1088> or <http://127.0.0.1:1088> by web browser.

LAN

1. Run **cmd.exe** and typed "**ipconfig**" command at local computer.
2. Get IP address from response.
3. Typed **http://ip:1088** (Example: **http://192.168.56.101:1088**) into web browser address bar at any computer in LAN.
4. If can't access, please check firewall rules.

```
CA Command Prompt
Microsoft Windows [Version 5.2.3790]
(C) Copyright 1985-2003 Microsoft Corp.

C:\Documents and Settings\Administrator>ipconfig

Windows IP Configuration

Ethernet adapter Local Area Connection:    IP Address

Connection-specific DNS Suffix  . : 
IP Address. . . . . : 192.168.56.101
Subnet Mask . . . . . : 255.255.255.0
Default Gateway . . . . . : 

C:\Documents and Settings\Administrator>_
```

Internet

If you're connected to internet directly, you can access management interface like LAN. if you're behind a router, make a port mapping from your computer to internet.

Search

Session List

Query sessions from start time to end time, view session details or play activity movie.

Search By Program or Window Title

Search sections by program name or window title, playback all related snapshots.

Search By Website or Url

Search sections by website url or url keyword, playback all related snapshots.

Search By Disk Drive or File Path

Search sections by disk drive or file path, playback all related snapshots.

Search

Sessions

Search Title

Search Url

Search File

Statistic

Config

Search Title x

Date From: 2013-11-07 To: 2013-11-07 User: Program: Title: Flash Search

	User	Date	Time	Program	Window Title	Snap Count	Movie
2013-11-07 - 2 Item(s)							
1	bfbf	2013-11-07	09:35 - 09:37	chrome	Adobe Flash Player	24	Play
2	bfbf	2013-11-07	09:40 - 09:40	chrome	Adobe Flash Player - chrome - Google Chrome		Play

localhost:1088/movie.htm?&sid=3a1465c8efc241be9c523259537d822d&title=ab69edd2798068928605717c6591462

Captain America: The Winter Soldier trailer LK - Ultimate Marvel HD

09:37:28

Copyright © 2013 www.ultragis.com All rights reserved.

Statistic

Computer Usage


Count user's busyness for hours in day.

Program Usage

Count frequency of use for program.

Website Visit

Count frequency of visit for website.



Configuration

System Parameters

System Parameters	
Parameter	Value
System Parameters	
Monitor Enabled	True
TrayIcon Visible	True
GrayScale Image	False
Access Rule	
Forbid Local Users	True
Permit Remote Address	192.168.0.99
Data Limit	
Disk Quote	0 GB
Days Persist	0 Days
LDAP Configuration	
Domain Name	ultragis.com
Manager Name	administrator
Manager Password	*****
Organizational Unit	

System Parameters

- **Monitor Enabled:** Enable or disable monitoring.
- **TrayIcon Visible:** Show or hide icon at notification bar.
- **GrayScale Image:** Store grayscale image for fewer disk space or colorful image for clear movie.

Access Rule

You can limit management interface access to user or computer by this parameters.

- **Forbid Local Users:** Only one user who installed Terminal Camera can visit <http://localhost:1088>.

- **Permit Remote Address:** Only permitted computer can visit management interface by <http://ip:1088>, and this parameter support ipv6 .
The example is: <http://192.168.0.99:1088>

Data Limit

You can limit data storage space by this parameters.

- **Disk Quote:** The disk quota for movie files. if overflow, delete old files automatically.
- **Days Persist:** The days number to keep movie file on disk. if expired, delete old files automatically.

LDAP Configuration

You can filter snapshots by Domain user or group.

- **Domain Name:** Domain name for LDAP query.
- **Manager Name:** LDAP query account.
- **Manager Password:** LDAP query password.
- **Organizational Unit:** Optional parameter for LDAP Organizational Unit.

Filter Policy

- **Users:** Select users to monitor or not monitor.

If LDAP Configuration parameters has been set, this panel will list domain users.

- **Groups:** Select user groups to monitor or not monitor.

If LDAP Configuration parameters has been set, this panel will list domain groups.

- **Program:** Select programs to monitor or not monitor.

License Info

View license info or register software by license key.

Admin Password

Change admin password for [login.htm](#).

Advanced Features

You can get advanced features by send e-mail to: support@ultragis.com.

JSON API

You can integrated Terminal Camera into custom interface or website by our JSON API.

Enterprise Version

Enterprise version store captured record from some agents into a data server.

[Home](#) | [Support](#)